

Electronic end limit venetian blind motor programing 55ZSE6 and 55ZSE9

You can program this motor only with it's Smart Home programing cable (5 meter long), connected with a hirschmann stecker.



- UP button
o
- DOWN button
- PROGRAM button

First we always programe the UP end limit: push down the UP button, and keep pushing it till You reach the UP end position what You want to have, than release the Up button, motor stops. (always before the emergency stop switch) Now, push down the „P” programe button and keep pushing it, till (7 seconds) the motor makes a up-down movement once. UP limit is finished now.

Than we can make the DOWN end limit: push down the DOWN button, and keep pushing it till You reach the DOWN end position what You want to have, than release the Up button, motor stops. (full close) Now, push down the „P” programe button and keep pushing it, till (7 seconds) the motor makes a up-down movement once. DOWN limit is finished now. We are ready with the full setting, now we can connect the wall switch or the external radio receiver.

We can change the end limits, only after we deleted all of them from the motor: now go somewhere middle position (beetwen the end limits). Push down the „P” programe button and the UP button together and keep them pushing for 3 seconds. Than let go the „P” programe button for 1 second. After the 1 second push down the „P” programe button again (the UP button still under pushing the whole time) and keep pushing them together till the motor makes an up-down movement twice. Now the delete is finished, You can start the programing again (with the UP limit firts).

Motor technical features:

- 4 minutes working time (before heating protection)
- 21 cm body lenght (shortest on the market)
- Emergency stop button
- Extra noisless: 55 dB
- 35 rpm (IP54)

