

DC256 installation and programing

It is a design radio receiver which You can connect to a switch motor. It works with the four channel DC115B keyring emitter after programing. And it has 3 button to use like a normal wall switch as well.

Push the wide plug in into the receiver, and connect the 4 wire with the motor four wire (colour to colour). Put on the 230 Voltage power.

The red led shows you that now You can use the DC256 like a normal wall switch.

Now push the P button on the left side of the emitter, and a green led starts flashing. Than push the STOP button on the receiver and the green led lights. Now push the right channel on the keyring emitter (the channel what You would like to program) and the green led turns off.

That is the end of the programing! You can learn more emitter the same way.

On the emitter: One push moves up, another push stops, another push moves downd the motor.



A DC256-ra 2 év gyártó garanciát vállalunk.

iroda:

H-1139 Budapest, Frangepán utca 79.

www.smart-home.hu | info@smart-home.hu | +36 20 287 1714

számlázási cím:

SANET-Trade Kft. | H-1139 Budapest, Petneházy utca 28.

Adószám: 14996429-2-41 | Bankszámlaszám: 10401000-50515755-88901018 K&H