

Electronic end limit venetian blind motor programing 55ZSE6 and 55ZSE9

(if the motor is connected from the right side (outside look))

You can program this motor only with it's Smart Home programing cable (5 meter long), connected with a hirschmann stecker.



- UP button
- o
- DOWN button
- PROGRAM button

First we always programe the DOWN end limit: push down the DOWN button, and keep pushing it till You reach the DOWN end position what You want to have, than release the DOWN button, motor stops. Now, push down the „P” programe button and keep pushing it, till (7 seconds) the motor makes a up-down movement once. DOWN limit is finished now.

Than we can make the UP end limit: push down the UP button, and keep pushing it till You reach the UP end position what You want to have, than release the Up button, motor stops. (Before reaching the emergency button) Now, push down the „P” programe button and keep pushing it, till (7 seconds) the motor makes a up-down movement once. UP limit is finished now. We are ready with the full setting, now we can connect the wall swith or the external radio receiver.

We can change the end limits, only after we deleted all of them from the motor: now go somewhere middle position (beetwen the end limits). Push down the „P” programe button and the DOWN button together and keep them pushing for 3 seconds. Than let go the „P” programe button for 1 second. After the 1 second, push down the „P” programe button again (the DOWN button still under pushing the whole time) and keep pushing them together till the motor makes an up-down movement twice. Now the delete is finished, You can start the programing again (with the DOWN limit firts).

Motor technical features:

- 4 minutes working time (before heating protection)
- 21 cm body lenght (shortest on the market)
- Emergency stop button
- Extra noisless: 55 dB
- 35 rpm (IP54)

